

# Universal Access Device 2<sup>next</sup>

## Universal Access Device 2<sup>next</sup> – All-Rounder for Debugging and Trace

The **Universal Access Device 2<sup>next</sup> (UAD2<sup>next</sup>)** is the new all-in-one device in PLS's UDE target access device family. It combines the state-of-the-art debugging features of the UAD2<sup>pro</sup> with trace capabilities, which makes it ideal for efficient debugging, test and system-level analysis. Together with the **Universal Debug Engine® (UDE)** the UAD2<sup>next</sup> provides a comprehensive and powerful support even for the latest heterogeneous multi-core SoCs.

- Fast and reliable access to AURIX 2nd Generation, AURIX, TriCore, PowerArchitecture, Cortex-R, Cortex-M, Cortex-A, XC2000, XE166, XMC1000, XMC4000, ARM7/9/11, SuperH SH-2A and RH850.
- Proven and robust aluminum housing 17.0 x 14.5 x 5.5 cm.
- Passive Cooling.

### High-Speed Target Access

The UAD2<sup>next</sup> is optimized for high-speed debug communication between UDE running on the host PC and the target system.

- Proven target adapter solution already used for UAD2<sup>pro</sup> and UAD3+ offers fastest and reliable target access for state-of-the-art debug interfaces **DAP, SWD, JTAG, cJTAG, LPD**.
- Ready for upcoming debug interfaces without replacing the base UAD2<sup>next</sup> device.
- High-speed debug access with up to **160 MHz shift clock** and **1.65 V – 5.5 V I/O voltage**.
- Galvanic isolated target adapters (RF coupler technology with 1,000 V<sub>RMS</sub> isolation) available.
- Longer distances between UAD2<sup>next</sup> and target system. Up to 0.5 m possible, 2.0 m on request.
- Connectors for **ASC** and **CAN/CAN FD<sup>\*)</sup>** with galvanic signal isolation up to 1,000 V<sub>RMS</sub>.
- Support for **DXCPL** (DAP over CAN Physical Layer).
- **USB3** or **Gigabit Ethernet** for connecting UAD2<sup>next</sup> to the PC.

#### At a Glance – The Universal Access Device 2<sup>next</sup>

- High performance debug access to AURIX 2nd Generation, AURIX TC2xxx, TriCore, PowerArchitecture, Cortex-R, -M, -A, XC2000, XE166, XMC4500, ARM7/9/11, SuperH SH-2A, RH850
- ASC and CAN/CAN FD<sup>\*)</sup> target interfaces
- Plug-in modules for parallel and serial trace
- 512 Mbyte internal trace memory
- USB3 and Gigabit Ethernet for connection to PC



### Trace Option

For trace based debugging, measurement and system-level analysis the UAD2<sup>next</sup> can be extended with target specific trace modules.

- Easy mounting plug-in modules for a wide range of trace interfaces.
- Up to 12 bit parallel trace.
- 2 Lane serial trace for up to 1.25 GBit/s.
- 512 Mbyte internal trace memory.
- Ready for ARM CoreSight ETM, STM, ITM, PTM, Xilinx FTM, for NEXUS class 3 parallel / serial AURORA trace and for Infineon MCDS.

<sup>\*)</sup> CAN FD available upon request.

#### If you have any questions about our products, please feel free to contact us:

PLS Programmierbare Logik & Systeme GmbH  
Technologiepark  
D – 02991 Lauta  
Germany

Phone: + 49 35722 384 – 0  
Fax: + 49 35722 384 – 69

PLS Development Tools  
19925 Stevens Creek Blvd  
Cupertino, CA 95014  
USA

Phone: +1 408 451 – 8408  
Fax: +1 408 501 – 8808  
Toll Free: +1 877 77DEBUG

**NeoMore**

5 rue de la Plaine  
78860 St Nom-la-Bretèche  
Tel. +33 1 30 64 15 81  
sales@neomore.com  
www.neomore.com  
www.moreneo.com

[www.pls-mc.com](http://www.pls-mc.com)  
[info@pls-mc.com](mailto:info@pls-mc.com)

**pls**  
Development Tools

2019\_0121